

JDYX2.E41599 - Fuses, Supplemental - Component

Fuses, Supplemental - Component

SCHURTER AG

Werkhofstrasse 8-12
 PO Box
 Lucerne, 6002 Switzerland

E41599

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
Supplemental fuses				
F1 5x20, FSF 5x20	5 x 20 (0.20 x 0.79)	0.032- 0.2	250Vac	35
		0.25- 3.15	250Vac	35
		4.0-8.0	250Vac	10x Ampere rating
		10.0- 10.0	250Vac	10x Ampere rating
FST 5x20, FSU 5x20, F1T	5 x 20 (0.20 x 0.79)	0.032- 0.04	250Vac	35
		0.05- 3.15	250Vac	35
		4.0- 16.0	250Vac	10x Ampere rating
FTT	5 x 20 (0.20 x 0.79)	0.063- 0.100	250Vac	35
		0.101- 4.0	250Vac	35

FTT (0.063A - 4A)	5 x 20 (0.20 x	0.101- 0.125	250Vac	35
--------------------------	-------------------	-----------------	--------	----

	0.79)			
		0.16-4	250Vac	35
		0.063-0.1	250Vac	35
OMT 125	-	0.0-.16	125Vac	100
		0.0-.16	125Vdc	100
Supplemental fuses: pigtail leads				
F1 5x20, FSF 5x20 (1331-0044(a))	5 x 20 (0.20 x 0.79)	0.032-0.2	250Vac	35
		0.25-3.15	250Vac	35
		4.0-8.0	250Vac	10x Ampere rating
FST	5.2 x 20 (0.20 x 0.79)	20-20	250Vac	200
FST 5x20, FSU 5x20, FIT (1331-0044 (a))	5 x 20 (0.20 x 0.79)	0.032-0.04	250Vac	35
		0.05-3.15	250Vac	35
		4.0-8.0	250Vac	10x Ampere rating
Supplemental fuses: pigtail leads, surface mount				
SPT 5x20, SSU 5x20 (1331.0044)	5 x 20 (0.20 x 0.79)	0.5-0.8	125Vac	10000
		0.5-0.8	250Vac	1500
		0.5-0.8	300Vdc	1500
		1.0-3.15	125Vac	10000
		1.0-3.15	250Vac	1500
		1.0-3.15	300Vdc	1500
		4.0-6.3	125Vac	10000

		4.0-6.3	250Vac	1500
		4.0-6.3	150Vdc	1500
		8.0-10	150Vdc	1500
		8.0-10	250Vac	1000
		12.5-16	125Vac	500
		12.5-16	125Vac	1000
		12.5-16	250Vac	500
		12.5-16	125Vdc	1500
Supplemental fuses: filled-tube				
FRT 250F	12 x 5 x 8 (0.47 x 0.20 x 0.31)	2.5-5.0	250Vac	63
		2.5-5.0	250Vdc	63
		6.3-10	250Vac	63
		0.16-0.8	250Vac	35
		0.16-0.8	250Vdc	35
		0.16-0.8	125Vac	10000
		1.0-2.0	250Vac	63
		1.0-2.0	250Vdc	63
		1.0-2.0	125Vac	10000
FRT 250T	12 x 5 x 8 (0.47 x 0.20 x 0.31)	0.16-0.63	250Vac	35
		0.16-0.63	250Vdc	35
		0.16-0.63	125Vac	10000
		0.8-2.0	250Vac	50

		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vdc	1000
		5-7.5	125Vdc	1000
		5-7.5	125Vdc	1000
		5-7.5	125Vdc	1000
		5-7.5	125Vdc	1000
		5-7.5	125Vdc	1000

		5-7.5	125Vdc	1000
		5-7.5	125Vdc	1000

		8-10	250Vac	1000
		8-10	150Vdc	1500
		12.5-16	125Vac	500
		12.5-16	125Vac	1000
		12.5-16	250Vac	500
		12.5-16	125Vdc	1500
SPT 5x20, SSU 5x20	5 x 20 (0.20 x 0.79)	0.5-0.8	125Vac	10000
		0.5-0.8	250Vac	1500
		0.5-0.8	300Vdc	1500
		1.0-3.15	125Vac	10000
		1.0-3.15	250Vac	1500
		1.0-3.15	300Vdc	1500
		4.0-6.3	125Vac	10000
		4.0-6.3	250Vac	1500
		4.0-6.3	150Vdc	1500
		8.0-10	150Vdc	1500
		8.0-10	250Vac	1000
		12.5-16	125Vac	500
		12.5-16	125Vac	1000
		12.5-16	250Vac	500
		12.5-16	125Vdc	1500

UMT-H	5.35 (0.20 x	0.05-2	277Vac	1500
--------------	-----------------	--------	--------	------

	0.79 x 0.21)			
		0.05-2	250Vdc	1500
		2.5-6.3	277Vac	1500
		2.5-6.3	125Vdc	1500
		8-10	250Vac	1500
		8-10	125Vdc	1500
		12.5- 12.5	250Vac	1000
		12.5- 12.5	125Vdc	1000
		16-16	250Vac	500
		16-16	125Vdc	500
UMT-M	15.85 x 5.35 x 5.35 (0.62 x 0.21 x 0.21)	16-16	250Vac	500
		16-16	125Vdc	500
UMT-W UMTW - 5316 - XXXXX - SMD - 0T - SN - 00 I II I - Series UMTW = Series UMT-W II - Rated Current 5A000 = 5 A 7A500 = 7.5 A 10A00 = 10 A 15A00 = 15 A 20A00 = 20 A	15.4 x 5.35 x 5.35 (0.61 x 0.21 x 0.21)	5-5	125Vac	350
		5-5	125Vdc	350
		7.5-7.5	125Vac	350
		7.5-7.5	125Vdc	350
		10-10	125Vac	350
		10-10	125Vdc	350
		15-15	125Vac	350
		15-15	125Vdc	350
		20-20	125Vac	350
		20-20	125Vdc	350
Supplemental fuses: filled-tube, surface mount, cartridge enclosed				
URT 250	10.9 x 3 x 3	2.5-2.5	277Vac	200

	(0.43 x 0.12 x 0.12)			
		2.5-2.5	250Vdc	100
		2.5-2.5	63Vdc	200
Supplemental fuses: pigtail leads				
SP 5x20 (1331-0044)	5 x 20 (0.20 x 0.79)	8-10	125Vac	10000
		8-10	250Vac	1500
		0.5-4	125Vac	10000
		0.5-4	250Vac	1500
		5-6.3	125Vac	10000
		5-6.3	250Vac	1500
Supplemental fuses: pigtail leads, filled-tube, cartridge enclosed				
SHF 6.3 x 32	6.35 x 32 (0.25 x 1.26)	1-1.6	500Vac	1500
		1-1.6	250Vac	1500
		1-1.6	125Vac	10000
		1-1.6	63Vdc	20000
		1-1.6	500Vdc	1500
		2-8	500Vac	1500
		2-8	250Vac	1500
		2-8	125Vac	10000
		2-8	63Vdc	20000
		2-8	400Vdc	1500
		10-16	500Vac	1500
		10-16	125Vac	10000
		10-16	250Vac	1500
		10-16	63Vdc	20000
		10-16	400Vdc	1500
		20-25	440Vac	1500
		20-25	63Vdc	20000

		20-25	63Vdc	20000
		20-25	250Vac	1500
		20-25	125Vac	10000
		32-32	125Vac	10000
		32-32	250Vac	1500
		32-32	440Vac	1500
		32-32	63Vdc	20000
		0.16-0.8	500Vac	1500
		0.16-0.8	250Vac	1500
		0.16-0.8	125Vac	10000
		0.16-0.8	500Vac	50000
		0.16-0.8	63Vdc	20000
		0.16-0.8	500Vdc	1500
SHT 6.3 x 32	6.35 x 32 (0.25 x 1.26)	0.5-2.5	500Vac	1500
		10-10	125Vac	10000
		10-10	63Vdc	20000
		10-10	400Vdc	1000
		12.5-16	400Vac	1500
		32-32	250Vac	1000
		20-25	250Vac	1000
		12.5-16	250Vac	1000
		12.5-32	125Vac	10000
		3.15-4	250Vac	1500

		5-8	250Vac	3500
--	--	-----	--------	------

		20-25	400Vac	1500
		32-32	400Vac	1500
		0.5-2.5	125Vac	10000
		0.5-2.5	63Vdc	20000
		0.5-2.5	400Vdc	1500
		3.15-8	125Vac	10000
		3.15-8	63Vdc	20000
		0.5-2.5	250Vac	1500
		3.15-4	400Vdc	1500
		3.15-8	500Vac	1500
		10-10	250Vac	1500
		10-10	500Vac	1500
Supplemental fuses: surface mount				
SMD - FST	5 x 20 (0.20 x 0.79)	0.032- 0.04	250Vac	35
		0.05- 3.15	250Vac	35
		4.0-8.0	250Vac	10x Ampere rating
		10.0- 16.0	250Vac	10x Ampere rating
SMD-FTT	5 x 20 (0.20 x 0.79)	0.063- 0.100	250Vac	35
		0.101- 4.0	250Vac	35
TF 600	3.2 x 10 (0.13 x 0.39)	0.5-2.0	600Vac	60
		0.5-2.0	125Vdc	60

UMF 250	2.45 (0.13 x	0.05-1	250Vac	200
----------------	-----------------	--------	--------	-----

	0.39 x 0.10)			
		0.05-1	125Vdc	200
		1.25-8	250Vac	100
		1.25-8	125Vdc	100
		10-10	250Vac	100
		10-10	125Vdc	500
		15-15	125Vac	150
		15-15	125Vdc	500
UMF 250 (Au)	10.9 x 3 x 3 (0.43 x 0.12 x 0.12)	0.05- 1.0	250Vac	200
		0.05- 1.0	125Vdc	200
		1.25- 4.0	250Vac	100
		1.25- 4.0	125Vdc	100
UMT 250	10.9 x 3 x 3 (0.43 x 0.12 x 0.12)	0.05-4	277Vac	200
		0.05-4	125Vdc	100
		0.05-4	250Vdc	35
		0.05-4	63Vac	200
		0.05-4	63Vdc	200
		5.0-6.3	250Vac	100
		5.0-6.3	125Vdc	100
		5.0-6.3	250Vdc	35
		5.0-6.3	63Vac	200
		5.0-6.3	63Vdc	200
		8.0- 10.0	250Vac	35
		8.0- 10.0	125Vdc	35

		8.0-10.0	63Vac	200
		8.0-10.0	63Vdc	200
UMT 250 (Au)	10.9 x 3 x 3 (0.43 x 0.12 x 0.12)	0.05-4	277Vac	200
		0.05-4	125Vdc	100
		0.05-4	250Vdc	35
		0.05-4	63Vac	200
		0.05-4	63Vdc	200
UMT-H rted 20-50A	15.85 x 5.35 x 5.35 (0.62 x 0.21 x 0.21)	20-30	125Vac	500
		20-30	250Vac	100
		20-30	72Vdc	500
		40-50	125Vac	500
		40-50	72Vdc	500
Supplemental fuses: surface mount, cartridge enclosed				
DRM-A (4A - 5A)	10.9 x 3 x 3 (0.43 x 0.12 x 0.12)	4-5	250Vac	100
		4-5	125Vdc	100
DRM-A (0.5A - 3A)	10.9 x 3 x 3 (0.43 x 0.12 x 0.12)	0.5-3	250Vac	100
		0.5-3	125Vdc	100

DRM-A (6.3A)	10.9 x 3 x 3	6.3-6.3	250Vac	100
---------------------	--------------	---------	--------	-----

	(0.43 x 0.12 x 0.12)			
		6.3-6.3	125Vdc	100
DRM-A (8 A)	10.9 x 3 x 3 (0.43 x 0.12 x 0.12)	8-8	250Vac	100
		8-8	125Vdc	100
Supplemental micro fuses				
MSA	-	0.625- 10	125Vdc	-
MSF 125, MSU 125	-	0.4-5	125Vac	100
		0.4-5	125Vdc	100
		0.35- 0.35	125Vac	100
		0.35- 0.35	125Vdc	100
		0.05- 0.315	125Vac	100
		0.05- 0.315	125Vdc	100
MSF 250	-	0.04-5	250Vac	35
		0.04-5	250Vac	10x Ampere rating
MST, MSU	-	0.04- 6.3	250Vac	35
		0.04- 6.3	250Vac	10x Ampere rating
		0.04- 6.3	63Vdc	50
		0.04- 6.3	63Vdc	10x Ampere rating
USF 0402	-	0.25-5	32Vdc	35
USF 0603	1.6 x 0.8 x	0.5-1.5	63Vac	50

	0.6 (0.06 x 0.03 x 0.02)			
		0.5-1.5	63Vdc	50
		1.75- 5.0	32Vac	50
		1.75- 5.0	32Vdc	50
Supplemental micro fuses: filled-tube				
MXT 250	-	0.04- 6.3	250Vac	100
Supplemental micro fuses: surface mount				
MGA, MGA-S	-	0.1-3	125Vac	50
		0.1-3	125Vdc	300
		4-4	63Vac	50
		4-4	125Vdc	50
		4-4	63Vdc	50
		4-4	32Vdc	300
		5-5	32Vac	50
		5-5	125Vdc	50
		5-5	32Vdc	300
MGA-A	-	0.1-3	125Vac	50
		0.1-3	125Vdc	300
		4-4	63Vac	50
		4-4	125Vdc	50
		4-4	63Vdc	50
		4-4	32Vdc	300
		5-5	32Vac	50
		5-5	125Vdc	50
		5-5	32Vdc	300

OMF 125, OSU 125	7.4 x 3.1 x	0.063- 3.15	125Vac	100
-------------------------	----------------	----------------	--------	-----

	2.6 (0.29 x 0.12 x 0.10)			
		0.063- 3.15	125Vdc	100
		3.5-5.0	125Vac	100
		3.5-5.0	125Vdc	100
		6.3-8.0	125Vac	100
		6.3-8.0	125Vdc	100
		10-10	125Vac	100
		10-10	125Vdc	100
		4.0-4.0	125Vac	100
		4.0-4.0	125Vdc	100
OMF 250, OSU 250	7.4 x 4.5 x 4.0 (0.29 x 0.18 x 0.16)	0.25-4	250Vac	100
		0.25-4	250Vdc	100
		0.4-0.4	400Vdc	50
OMF 63	7.4 x 3.1 x 2.5 (0.29 x 0.12 x 0.10)	0.063- 5.0	63Vac	50
		0.063- 5.0	63Vdc	50
		6.3-8.0	63Vac	50
		6.3-8.0	63Vdc	50
		10-10	63Vac	50
		10-10	63Vdc	50

OMT	7.4 x 4.5 x	0.5- 1.25	250Vac	100
------------	----------------	--------------	--------	-----

	4.0 (0.29 x 0.18 x 0.16)			
		0.5- 1.25	125Vdc	100
		1.5-2.0	250Vac	50
		1.5-2.0	125Vac	100
		1.5-2.0	125Vdc	100
		2.5-5.0	125Vac	100
		2.5-5.0	125Vdc	100
USF 1206	3.2 x 1.6 x 0.6 (0.13 x 0.06 x 0.02)	0.75-4	32Vac	50
		0.75-4	63Vdc	50
		0.375- 0.5	125Vac	50
		0.375- 0.5	125Vdc	50
USFF 1206	3.2 x 1.6 x 1.6 (0.13 x 0.06 x 0.06)	0.05- 0.25	125Vac	10
		0.05- 0.25	63Vdc	100
		0.05- 0.25	32Vac	100
USI 1206	3.2 x 1.6 x 0.6 (0.13 x 0.06 x 0.02)	0.4-6.3	32Vac	63
		0.4-6.3	63Vdc	63

USL 0603	1.6 x 0.8 x	0.035- 0.05	63Vdc	50
-----------------	----------------	----------------	-------	----

	0.5 (0.06 x 0.03 x 0.02)			
UST 1206	3.2 x 1.62 x 1.62 (0.13 x 0.06 x 0.06)	5-25	32Vac	100
		5-25	63Vdc	100
		5-25	24Vac	150
		5-25	42Vdc	400

(a) - Push-on pig tail assemblies 1331-0044 may be provided for fuses FST 5x20, SMD-FST, FSU 5x20, F1T, F1 5x20, FSF 5x20, SP 5x20, FA1 5x20, SMD-SPT, SPT 5x20, SSU 5x20. The rating can be up to 16 Amps for the last five fuses.

Marking: Company name or tradename "S in a square" and model designation.

Last Updated on 2022-10-18



The appearance of a company's name or product in this database does not in itself assure that products so identified have been manufactured under UL Solutions' Follow - Up Service. Only those products bearing the UL Mark should be considered to be Certified and covered under UL Solutions' Follow - Up Service. Always look for the Mark on the product.

UL Solutions permits the reproduction of the material contained in Product iQ subject to the following conditions: 1. The Guide Information, Assemblies, Constructions, Designs, Systems, and/or Certifications (files) must be presented in their entirety and in a non-misleading manner, without any manipulation of the data (or drawings). 2. The statement "Reprinted from Product iQ with permission from UL Solutions" must appear adjacent to the extracted material. In addition, the reprinted material must include a copyright notice in the following format: "©2022 UL LLC."

JDYX8.E41599 - Fuses, Supplemental Certified for Canada - Component

Fuses, Supplemental Certified for Canada - Component

SCHURTER AG

Werkhofstrasse 8-12
 PO Box
 Lucerne, 6002 Switzerland

E41599

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
Supplemental fuses				
F1 5x20, FSF 5x20	5 x 20 (0.20 x 0.79)	0.032- 0.2	250Vac	35
		0.25- 3.15	250Vac	35
		4.0-8.0	250Vac	10x Ampere rating
		10.0- 10.0	250Vac	10x Ampere rating
FST 5x20, FSU 5x20, F1T	5 x 20 (0.20 x 0.79)	0.032- 0.04	250Vac	35
		0.05- 3.15	250Vac	35
		4.0- 16.0	250Vac	10x Ampere rating
FTT	5 x 20 (0.20 x 0.79)	0.063- 0.100	250Vac	35
		0.101- 4.0	250Vac	35
FTT (0.063A - 4A)	5 x 20 (0.20 x	0.101- 0.125	250Vac	35

	0.79)			
		0.16-4	250Vac	35
		0.063-0.1	250Vac	35
OMT 125	-	0.0-.16	125Vac	100
		0.0-.16	125Vdc	100
Supplemental fuses: pigtail leads				
F1 5x20, FSF 5x20 (1331-0044(a))	5 x 20 (0.20 x 0.79)	0.032-0.2	250Vac	35
		0.25-3.15	250Vac	35
		4.0-8.0	250Vac	10x Ampere rating
FST	5.2 x 20 (0.20 x 0.79)	20-20	250Vac	200
FST 5x20, FSU 5x20, FIT (1331-0044 (a))	5 x 20 (0.20 x 0.79)	0.032-0.04	250Vac	35
		0.05-3.15	250Vac	35
		4.0-8.0	250Vac	10x Ampere rating
Supplemental fuses: pigtail leads, surface mount				
SPT 5x20, SSU 5x20 (1331.0044)	5 x 20 (0.20 x 0.79)	0.5-0.8	125Vac	10000
		0.5-0.8	250Vac	1500
		0.5-0.8	300Vdc	1500
		1.0-3.15	125Vac	10000
		1.0-3.15	250Vac	1500
		1.0-3.15	300Vdc	1500
		4.0-6.3	125Vac	10000

		4.0-6.3	250Vac	1500
		4.0-6.3	150Vdc	1500
		8.0-10	150Vdc	1500
		8.0-10	250Vac	1000
		12.5-16	125Vac	500
		12.5-16	125Vac	1000
		12.5-16	250Vac	500
		12.5-16	125Vdc	1500
Supplemental fuses: filled-tube				
FRT 250F	12 x 5 x 8 (0.47 x 0.20 x 0.31)	2.5-5.0	250Vac	63
		2.5-5.0	250Vdc	63
		6.3-10	250Vac	63
		0.16-0.8	250Vac	35
		0.16-0.8	250Vdc	35
		0.16-0.8	125Vac	10000
		1.0-2.0	250Vac	63
		1.0-2.0	250Vdc	63
		1.0-2.0	125Vac	10000
FRT 250T	12 x 5 x 8 (0.47 x 0.20 x 0.31)	0.16-0.63	250Vac	35
		0.16-0.63	250Vdc	35
		0.16-0.63	125Vac	10000
		0.8-2.0	250Vac	50

		0.8-2.0	250Vdc	50
		0.8-2.0	125Vac	10000
		2.5-5.0	250Vac	50
		6.3-10	250Vac	63
SP 5x20	5 x 20 (0.20 x 0.79)	8-10	125Vac	10000
		8-10	250Vac	1500
		12.5- 16	125Vac	50
		12.5- 16	125Vac	1000
		12.5- 16	250Vac	500
		0.5-4	125Vac	10000
		0.5-4	250Vac	1500
		5-6.3	125Vac	10000
		5-6.3	250Vac	1500

Supplemental fuses: filled-tube, surface mount

HCF	2.09 x 5 x 5 (0.08 x 0.20 x 0.20)	5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200
		5-7.5	125Vac	200

		5-7.5	125Vac	200
		5-7.5	125Vac	200

		12.5-16	125Vdc	1500
SPT 5x20, SSU 5x20	5 x 20 (0.20 x 0.79)	0.5-0.8	125Vac	10000
		0.5-0.8	250Vac	1500
		0.5-0.8	300Vdc	1500
		1.0-3.15	125Vac	10000
		1.0-3.15	250Vac	1500
		1.0-3.15	300Vdc	1500
		4.0-6.3	125Vac	10000
		4.0-6.3	250Vac	1500
		4.0-6.3	150Vdc	1500
		8.0-10	150Vdc	1500
		8.0-10	250Vac	1000
		12.5-16	125Vac	500
		12.5-16	125Vac	1000
		12.5-16	250Vac	500
		12.5-16	125Vdc	1500
UMT-H	5.35 (0.20 x 0.79 x 0.21)	0.05-2	277Vac	1500
		0.05-2	250Vdc	1500
		2.5-6.3	277Vac	1500
		2.5-6.3	125Vdc	1500
		8-10	250Vac	1500
		8-10	125Vdc	1500

		12.5-12.5	250Vac	1000
--	--	-----------	--------	------

		12.5-12.5	125Vdc	1000
		16-16	250Vac	500
		16-16	125Vdc	500
UMT-M	15.85 x 5.35 x 5.35 (0.62 x 0.21 x 0.21)	16-16	250Vac	500
		16-16	125Vdc	500
UMT-W UMTW - 5316 - XXXXX - SMD - 0T - SN - 00 I II I - Series UMTW = Series UMT-W II - Rated Current 5A000 = 5 A 7A500 = 7.5 A 10A00 = 10 A 15A00 = 15 A 20A00 = 20 A	15.4 x 5.35 x 5.35 (0.61 x 0.21 x 0.21)	5-5	125Vac	350
		5-5	125Vdc	350
		7.5-7.5	125Vac	350
		7.5-7.5	125Vdc	350
		10-10	125Vac	350
		10-10	125Vdc	350
		15-15	125Vac	350
		15-15	125Vdc	350
		20-20	125Vac	350
		20-20	125Vdc	350
Supplemental fuses: filled-tube, surface mount, cartridge enclosed				
URT 250	10.9 x 3 x 3 (0.43 x 0.12 x 0.12)	2.5-2.5	277Vac	200
		2.5-2.5	250Vdc	100
		2.5-2.5	63Vdc	200
Supplemental fuses: pigtail leads				

SP 5x20 (1331-0044)	5 x 20 (0.20 x	8-10	125Vac	10000
----------------------------	-------------------	------	--------	-------

	0.79)			
		8-10	250Vac	1500
		0.5-4	125Vac	10000
		0.5-4	250Vac	1500
		5-6.3	125Vac	10000
		5-6.3	250Vac	1500

Supplemental fuses: pigtail leads, filled-tube, cartridge enclosed

SHF 6.3 x 32	6.35 x 32 (0.25 x 1.26)	1-1.6	500Vac	1500
		1-1.6	250Vac	1500
		1-1.6	125Vac	10000
		1-1.6	63Vdc	20000
		1-1.6	500Vdc	1500
		2-8	500Vac	1500
		2-8	250Vac	1500
		2-8	125Vac	10000
		2-8	63Vdc	20000
		2-8	400Vdc	1500
		10-16	500Vac	1500
		10-16	125Vac	10000
		10-16	250Vac	1500
		10-16	63Vdc	20000
		10-16	400Vdc	1500
		20-25	440Vac	1500
		20-25	63Vdc	20000
		20-25	250Vac	1500
		20-25	125Vac	10000
		32-32	125Vac	10000
		32-32	250Vac	1500

		32-32	440Vac	1500
		32-32	63Vdc	20000

		32-32	63Vdc	20000
		0.16-0.8	500Vac	1500
		0.16-0.8	250Vac	1500
		0.16-0.8	125Vac	10000
		0.16-0.8	500Vac	50000
		0.16-0.8	63Vdc	20000
		0.16-0.8	500Vdc	1500
SHT 6.3 x 32	6.35 x 32 (0.25 x 1.26)	0.5-2.5	500Vac	1500
		10-10	125Vac	10000
		10-10	63Vdc	20000
		10-10	400Vdc	1000
		12.5-16	400Vac	1500
		32-32	250Vac	1000
		20-25	250Vac	1000
		12.5-16	250Vac	1000
		12.5-32	125Vac	10000
		3.15-4	250Vac	1500
		5-8	250Vac	3500
		20-25	400Vac	1500
		32-32	400Vac	1500
		0.5-2.5	125Vac	10000
		0.5-2.5	63Vdc	20000
		0.5-2.5	400Vdc	1500

		3.15-8	125Vac	10000
		0.16-0.8	500Vdc	50000

		3.15-8	63Vdc	20000
		0.5-2.5	250Vac	1500
		3.15-4	400Vdc	1500
		3.15-8	500Vac	1500
		10-10	250Vac	1500
		10-10	500Vac	1500
Supplemental fuses: surface mount				
SMD - FST	5 x 20 (0.20 x 0.79)	0.032- 0.04	250Vac	35
		0.05- 3.15	250Vac	35
		4.0-8.0	250Vac	10x Ampere rating
		10.0- 16.0	250Vac	10x Ampere rating
SMD-FTT	5 x 20 (0.20 x 0.79)	0.063- 0.100	250Vac	35
		0.101- 4.0	250Vac	35
TF 600	3.2 x 10 (0.13 x 0.39)	0.5-2.0	600Vac	60
		0.5-2.0	125Vdc	60
UMF 250	2.45 (0.13 x 0.39 x 0.10)	0.05-1	250Vac	200
		0.05-1	125Vdc	200
		1.25-8	250Vac	100
		1.25-8	125Vdc	100
		10-10	250Vac	100
		10-10	125Vdc	500
		15-15	125Vac	150
		15-15	125Vdc	500

		15-15	125Vdc	500
UMF 250 (Au)	10.9 x 3 x 3 (0.43 x 0.12 x 0.12)	0.05- 1.0	250Vac	200
		0.05- 1.0	125Vdc	200
		1.25- 4.0	250Vac	100
		1.25- 4.0	125Vdc	100
UMT 250	10.9 x 3 x 3 (0.43 x 0.12 x 0.12)	0.05-4	277Vac	200
		0.05-4	125Vdc	100
		0.05-4	250Vdc	35
		0.05-4	63Vac	200
		0.05-4	63Vdc	200
		5.0-6.3	250Vac	100
		5.0-6.3	125Vdc	100
		5.0-6.3	250Vdc	35
		5.0-6.3	63Vac	200
		5.0-6.3	63Vdc	200
		8.0- 10.0	250Vac	35
		8.0- 10.0	125Vdc	35
		8.0- 10.0	63Vac	200
		8.0- 10.0	63Vdc	200
UMT 250 (Au)	10.9 x 3 x 3 (0.43 x 0.12 x 0.12)	0.05-4	277Vac	200
		0.05-4	125Vdc	100

		0.05-4	250Vdc	35
		0.05-4	63Vac	200
		0.05-4	63Vdc	200
UMT-H rted 20-50A	15.85 x 5.35 x 5.35 (0.62 x 0.21 x 0.21)	20-30	125Vac	500
		20-30	250Vac	100
		20-30	72Vdc	500
		40-50	125Vac	500
		40-50	72Vdc	500
Supplemental fuses: surface mount, cartridge enclosed				
DRM-A (4A - 5A)	10.9 x 3 x 3 (0.43 x 0.12 x 0.12)	4-5	250Vac	100
		4-5	125Vdc	100
DRM-A (0.5A - 3A)	10.9 x 3 x 3 (0.43 x 0.12 x 0.12)	0.5-3	250Vac	100
		0.5-3	125Vdc	100
DRM-A (6.3A)	10.9 x 3 x 3 (0.43 x 0.12 x 0.12)	6.3-6.3	250Vac	100
		6.3-6.3	125Vdc	100
DRM-A (8 A)	10.9 x 3 x 3 (0.43 x 0.12 x 0.12)	8-8	250Vac	100
		8-8	125Vdc	100
Supplemental micro fuses				
MSF 125, MSU 125	-	0.4-5	125Vac	100
		0.4-5	125Vdc	100

		0.4-5	125Vdc	100
		0.35-0.35	125Vac	100
		0.35-0.35	125Vdc	100
		0.05-0.315	125Vac	100
		0.05-0.315	125Vdc	100
MSF 250	-	0.04-5	250Vac	35
		0.04-5	250Vac	10x Ampere rating
MST, MSU	-	0.04-6.3	250Vac	35
		0.04-6.3	250Vac	10x Ampere rating
		0.04-6.3	63Vdc	50
		0.04-6.3	63Vdc	10x Ampere rating
USF 0603	1.6 x 0.8 x 0.6 (0.06 x 0.03 x 0.02)	0.5-1.5	63Vac	50
		0.5-1.5	63Vdc	50
		1.75-5.0	32Vac	50
		1.75-5.0	32Vdc	50
Supplemental micro fuses: filled-tube				
MXT 250	-	0.04-6.3	250Vac	100
Supplemental micro fuses: surface mount				
MGA, MGA-S	-	0.1-3	125Vac	50
		0.1-3	125Vdc	300
		0.1-3	63Vdc	50

		4-4	63Vac	50
		4-4	125Vdc	50
		4-4	63Vdc	50
		4-4	32Vdc	300
		5-5	32Vac	50
		5-5	125Vdc	50
		5-5	32Vdc	300
MGA-A	-	0.1-3	125Vac	50
		0.1-3	125Vdc	300
		4-4	63Vac	50
		4-4	125Vdc	50
		4-4	63Vdc	50
		4-4	32Vdc	300
		5-5	32Vac	50
		5-5	125Vdc	50
		5-5	32Vdc	300
OMF 125, OSU 125	7.4 x 3.1 x 2.6 (0.29 x 0.12 x 0.10)	0.063- 3.15	125Vac	100
		0.063- 3.15	125Vdc	100
		3.5-5.0	125Vac	100
		3.5-5.0	125Vdc	100
		6.3-8.0	125Vac	100
		6.3-8.0	125Vdc	100
		10-10	125Vac	100
		10-10	125Vdc	100
		4.0-4.0	125Vac	100
		4.0-4.0	125Vdc	100

OMF 250, OSU 250	7.4 x 4.5 x	0.25-4	250Vac	100
-------------------------	----------------	--------	--------	-----

	4.0 (0.29 x 0.18 x 0.16)			
		0.25-4	250Vdc	100
		0.4-0.4	400Vdc	50
OMF 63	7.4 x 3.1 x 2.5 (0.29 x 0.12 x 0.10)	0.063- 5.0	63Vac	50
		0.063- 5.0	63Vdc	50
		6.3-8.0	63Vac	50
		6.3-8.0	63Vdc	50
		10-10	63Vac	50
		10-10	63Vdc	50
OMT	7.4 x 4.5 x 4.0 (0.29 x 0.18 x 0.16)	0.5- 1.25	250Vac	100
		0.5- 1.25	125Vdc	100
		1.5-2.0	250Vac	50
		1.5-2.0	125Vac	100
		1.5-2.0	125Vdc	100
		2.5-5.0	125Vac	100
		2.5-5.0	125Vdc	100
USF 1206	3.2 x 1.6 x 0.6 (0.13 x 0.06 x 0.02)	0.75-4	32Vac	50
		0.75-4	63Vdc	50

		0.375- 0.5	125Vac	50
--	--	---------------	--------	----

		0.375-0.5	125Vdc	50
USFF 1206	3.2 x 1.6 x 1.6 (0.13 x 0.06 x 0.06)	0.05-0.25	125Vac	10
		0.05-0.25	63Vdc	100
		0.05-0.25	32Vac	100
USI 1206	3.2 x 1.6 x 0.6 (0.13 x 0.06 x 0.02)	0.4-6.3	32Vac	63
		0.4-6.3	63Vdc	63
USL 0603	1.6 x 0.8 x 0.5 (0.06 x 0.03 x 0.02)	0.035-0.05	63Vdc	50
UST 1206	3.2 x 1.62 x 1.62 (0.13 x 0.06 x 0.06)	5-25	32Vac	100
		5-25	63Vdc	100
		5-25	24Vac	150
		5-25	42Vdc	400

(a) - Push-on pig tail assemblies 1331-0044 may be provided for fuses FST 5x20, SMD-FST, FSU 5x20, F1T, F1 5x20, FSF 5x20, SP 5x20, FA1 5x20, SMD-SPT, SPT 5x20, SSU 5x20. The rating can be up to 16 Amps for the last five fuses.

Marking: Company name or tradename "S in a square", model designation and the Recognized Component Mark for Canada,



Last Updated on 2022-10-18



The appearance of a company's name or product in this database does not in itself assure that products so identified have been manufactured under UL Solutions' Follow - Up Service. Only those products bearing the UL Mark should be considered to be Certified and covered under UL Solutions' Follow - Up Service. Always look for the Mark on the product.

UL Solutions permits the reproduction of the material contained in Product iQ subject to the following conditions: 1. The Guide Information, Assemblies, Constructions, Designs, Systems, and/or Certifications (files) must be presented in their entirety and in a non-misleading manner, without any manipulation of the data (or drawings). 2. The statement "Reprinted from Product iQ with permission from UL Solutions" must appear adjacent to the extracted material. In addition, the reprinted material must include a copyright notice in the following format: "©2022 UL LLC."