

84331104 / K31S10A:
Cable-mounted Connector

Rev.11-24-2014

Assembly Instructions:

- Select cable size—see chart at right.
- Strip length:
Outer jacket: 35mm, Ground: 16mm, Line: 10mm, Neutral: 10mm
- Remove bottom shell of connector.
- Loosen nut and slide back shell onto cable.
- Connect wires to contact assembly per wiring diagram at right, complying with tightening torque figures in chart at right.
- Reassemble back shell to contact assembly. Turn contact assembly clockwise to lock. Tighten cable nut according to torque chart.

Torque					
Screw Terminals			Cable Nut		
Nm.	ft./lb.	in./lb.	Nm.	ft./lb.	in./lb.
1.0	0.7	5.0	4.0	3.0	35.4
Recommended Wire Size					
North American					
12AWG					
North American Wiring					



100 Interpower Avenue
Oskaloosa, IA 52577 (U.S.A.)
Toll-free-telephone: (800)662-2290
Toll-free FAX: (800) 645-5360