

JDYX2.E167295 - Fuses, Supplemental - Component

Fuses, Supplemental - Component

SIBA GmbHBorker Strasse 20-22
Luenen, 44534 Germany

E167295

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
Supplemental fuses				
179020, 179020 SMD	5 x 20 (0.20 x 0.79)	0.032-0.4	250Vac	35
		0.032-0.4	250Vac	10x Ampere rating
		0.5-6.3	250Vac	35
		0.5-6.3	250Vac	10x Ampere rating
179120, 179120 SMD	5 x 20 (0.20 x 0.79)	0.032-0.1	250Vac	35
		0.032-0.1	250Vac	10x Ampere rating
		0.11-0.5	250Vac	35
		0.11-0.5	250Vac	10x Ampere rating
		0.63-6.3	250Vac	35
		0.63-6.3	250Vac	10x Ampere rating
189020, 189020.SMD	6.35 x 32 (0.25 x 1.26)	0.16-6.3	500Vac	50000
		0.16-6.3	450Vdc	1500
189120.32	32 x 6.3 (1.26 x 0.25)	32-32	305Vac	1500
189120.32 SMD	32 x 6.3 (1.26 x 0.25)	32-32	305Vac	1500
189140.32SA	32 x 6.3 (1.26 x 0.25)	32-32	305Vac	1500
189140.32SA SMD	32 x 6.3 (1.26 x 0.25)	32-32	305Vac	1500
70 065 63	6.35 x 32 (0.25 x 1.26)	0.16-6.3	500Vac	50000

		0.16-6.3	450Vdc	1500
7012570	32 x 6.3 (1.26 x 0.25)	10-16	630Vac	1500
7012570.SMD	32 x 6.3 (1.26 x 0.25)	10-16	630Vac	1500
FUSE 0402/151000	0.32 x 1.0 x 0.5 (0.01 x 0.04 x 0.02)	0.5-3.15	32Vdc	50
FUSE 0603/152000	0.45 x 1.55 x 0.85 (0.02 x 0.06 x 0.03)	0.5-4.0	32Vac	50
FUSE 0805/153000	0.45 x 2.0 x 1.25 (0.02 x 0.08 x 0.05)	0.5-4.0	32Vac	50
FUSE 1206/154000	0.55 x 3.2 x 1.6 (0.02 x 0.13 x 0.06)	0.5-6.3	63Vac	50
		0.5-6.3	63Vdc	50
Supplemental fuses: filled-tube				
160016, 160016.Au	16 x 4.4 x 4.4 (0.63 x 0.17 x 0.17)	12.5-20	125Vac	1000
		12.5-20	125Vdc	1500
		0.05-4	305Vac	1500
		5-6.3	277Vac	1500
		8-10	250Vac	1500
		0.05-10	250Vdc	1500
179021, 179021.SMD	-	0.2-0.8	250Vac	1500
		1-10	250Vac	1500
179200	5 x 20 (0.20 x 0.79)	8-10	250Vac	4000
179200, 179200.SMD	5 x 20 (0.20 x 0.79)	0.05-0.8	250Vac	1500
		1.0-1.6	250Vac	1500
		2.0-3.15	250Vac	1500
		4.0-6.3	250Vac	1500
		1.0-3.15	300Vdc	1500
		4.0-4.0	300Vdc	1500
189140, 189140.SMD	6.35 x 32 (0.25 x 1.26)	0.1-0.4	500Vac	1500
		0.5-2.5	500Vac	1500

		3.15-16	500Vac	1500
		3.15-16	400Vdc	1500
189140.16SA	6.3 x 32 (0.25 x 1.26)	16-16	500Vac	36000
70 007 65	5 x 20 (0.20 x 0.79)	8-10	250Vac	4000
70 065 65, 70 065.65.SMD	6.35 x 32 (0.25 x 1.26)	0.1-0.4	500Vac	1500
		0.5-2.5	500Vac	1500
		3.15-16	500Vac	1500
		3.15-16	400Vdc	1500
7012565	32 x 6.3 (1.26 x 0.25)	10-16	530Vac	5000
7017240	32 x 6.3 (1.26 x 0.25)	0.1-0.5	1000Vac	30000
		0.63-1.6	1000Vac	30000
		0.1-0.5	1000Vdc	30000
		0.63-1.6	1000Vdc	30000
		2-2	1000Vdc	30000
7017250	6.3 x 32 (0.25 x 1.26)	0.5-1	800Vdc	30,000
7017250.SMD	6.3 x 32 (0.25 x 1.26)	0.5-1	800Vdc	30,000
Supplemental fuses: filled-tube, cartridge enclosed				
7012540	-	0.1-1	700Vac	50000
		1.25-2	700Vac	50000
		2.25-5	600Vac	50000
		6.3-10	600Vac	50000
		12.5-25	500Vac	50000
Supplemental fuses: filled-tube, surface mount "160020"				
160020	20 x 5.8 x 5.8 (0.79 x 0.23 x 0.23)	3.15-20	250Vdc	1500
		3.15-16	277Vac	1500
		20-20	250Vac	1500
Supplemental fuses: filled-tube, surface mount				

7002563.16 SMD	6.3 x 32 (0.25 x 1.26)	16-16	250Vac	2000
		16-16	300Vdc	2000
7002563.16AK	6.3 x 32 (0.25 x 1.26)	16-16	250Vac	2000
		16-16	300Vdc	2000
7002563.16AK-SA	6.3 x 32 (0.25 x 1.26)	16-16	250Vac	2000
		16-16	300Vdc	2000
7012565.SMD	32 x 6.3 (1.26 x 0.25)	10-16	530Vac	5000
Supplemental micro fuses: filled-tube				
160000	4.4 x 8.0 (0.17 x 0.31)	0.032-5	250Vac	100
		0.032-5	72Vdc	100
7006585, 7006585.SMD	-	6.3-20	500Vac	1,500
Supplemental micro fuses: surface mount				
157000	2.6 x 6.1 (0.10 x 0.24)	0.062-7.0	125Vac	50
		0.062-7.0	125Vdc	50
		8-15	65Vac	50
		8-15	65Vdc	50
158000	2.6 x 6.1 (0.10 x 0.24)	0.25-6.3	65Vdc	50
		0.25-6.3	125Vac	50
		0.25-6.3	32Vdc	300
159000 (+)	2.6 x 6.1 (0.10 x 0.24)	0.315-0.57	250Vac	10
7016974	2.6 x 6.1 (0.10 x 0.24)	0.062-7	125Vac	50
		0.062-7	125Vdc	50
		8-15	65Vac	50
		8-15	65Vdc	50
7016975	2.6 x 6.1 (0.10 x 0.24)	0.25-6.3	65Vdc	50
		0.25-6.3	125Vac	50

		0.25-6.3	32Vdc	300
Supplemental micro fuses: surface mount, cartridge enclosed				
169000.AM	8 x 4.4 x 4.399 (0.31 x 0.17 x 0.17)	0.63-6.3	250Vac	20

(+) - Followed by ampere rating

[Click here to view the Colombia Market Access Certification](#)

[Click here to view the Ecuador Market Access Certification](#)

Marking: Company name or trademark  and model designation.

Last Updated on 2021-08-18

The appearance of a company's name or product in this database does not in itself assure that products so identified have been manufactured under UL's Follow-Up Service. Only those products bearing the UL Mark should be considered to be Certified and covered under UL's Follow-Up Service. Always look for the Mark on the product.

UL permits the reproduction of the material contained in the Online Certification Directory subject to the following conditions: 1. The Guide Information, Assemblies, Constructions, Designs, Systems, and/or Certifications (files) must be presented in their entirety and in a non-misleading manner, without any manipulation of the data (or drawings). 2. The statement "Reprinted from the Online Certifications Directory with permission from UL" must appear adjacent to the extracted material. In addition, the reprinted material must include a copyright notice in the following format: "© 2022 UL LLC"

JDYX8.E167295 - Fuses, Supplemental Certified for Canada - Component

Fuses, Supplemental Certified for Canada - Component

SIBA GmbH

Borker Strasse 20-22
Luenen, 44534 Germany

E167295

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
Supplemental fuses				
179020, 179020 SMD	5 x 20 (0.20 x 0.79)	0.032-0.4	250Vac	35
		0.032-0.4	250Vac	10x Ampere rating
		0.5-6.3	250Vac	35
		0.5-6.3	250Vac	10x Ampere rating
179120, 179120 SMD	5 x 20 (0.20 x 0.79)	0.032-0.1	250Vac	35
		0.032-0.1	250Vac	10x Ampere rating
		0.11-0.5	250Vac	35
		0.11-0.5	250Vac	10x Ampere rating
		0.63-6.3	250Vac	35
		0.63-6.3	250Vac	10x Ampere rating
189020, 189020.SMD	6.35 x 32 (0.25 x 1.26)	0.16-6.3	500Vac	50000
		0.16-6.3	450Vdc	1500
189120.32	32 x 6.3 (1.26 x 0.25)	32-32	305Vac	1500
189120.32 SMD	32 x 6.3 (1.26 x 0.25)	32-32	305Vac	1500
189140.32SA	32 x 6.3 (1.26 x 0.25)	32-32	305Vac	1500
189140.32SA SMD	32 x 6.3 (1.26 x 0.25)	32-32	305Vac	1500

7012570	32 x 6.3 (1.26 x 0.25)	10-16	630Vac	1500
7012570.SMD	32 x 6.3 (1.26 x 0.25)	10-16	630Vac	1500
FUSE 0402/151000	0.32 x 1.0 x 0.5 (0.01 x 0.04 x 0.02)	0.5-3.15	32Vdc	50
FUSE 0603/152000	0.45 x 1.55 x 0.85 (0.02 x 0.06 x 0.03)	0.5-4.0	32Vac	50
FUSE 0805/153000	0.45 x 2.0 x 1.25 (0.02 x 0.08 x 0.05)	0.5-4.0	32Vac	50
FUSE 1206/154000	0.55 x 3.2 x 1.6 (0.02 x 0.13 x 0.06)	0.5-6.3	63Vac	50
		0.5-6.3	63Vdc	50
Supplemental fuses: filled-tube				
160016, 160016.Au	16 x 4.4 x 4.4 (0.63 x 0.17 x 0.17)	12.5-20	125Vac	1000
		12.5-20	125Vdc	1500
		0.05-4	305Vac	1500
		5-6.3	277Vac	1500
		8-10	250Vac	1500
		0.05-10	250Vdc	1500
179021, 179021.SMD	-	0.2-0.8	250Vac	1500
		1-10	250Vac	1500
179200	5 x 20 (0.20 x 0.79)	8-10	250Vac	4000
179200, 179200.SMD	5 x 20 (0.20 x 0.79)	0.05-0.8	250Vac	1500
		1.0-1.6	250Vac	1500
		2.0-3.15	250Vac	1500
		4.0-6.3	250Vac	1500
		1.0-3.15	300Vdc	1500
		4.0-4.0	300Vdc	1500
189140, 189140.SMD	6.35 x 32 (0.25 x 1.26)	0.1-0.4	500Vac	1500
		0.5-2.5	500Vac	1500
		3.15-16	500Vac	1500

		3.15-16	400Vdc	1500
189140.16SA	6.3 x 32 (0.25 x 1.26)	16-16	500Vac	36000
70 065 65, 70 065.65.SMD	6.35 x 32 (0.25 x 1.26)	0.1-0.4	500Vac	1500
		0.5-2.5	500Vac	1500
		3.15-16	500Vac	1500
		3.15-16	400Vdc	1500
7012565	32 x 6.3 (1.26 x 0.25)	10-16	530Vac	5000
7017240	32 x 6.3 (1.26 x 0.25)	0.1-0.5	1000Vac	30000
		0.63-1.6	1000Vac	30000
		0.1-0.5	1000Vdc	30000
		0.63-1.6	1000Vdc	30000
		2-2	1000Vdc	30000
7017250	6.3 x 32 (0.25 x 1.26)	0.5-1	800Vdc	30,000
7017250.SMD	6.3 x 32 (0.25 x 1.26)	0.5-1	800Vdc	30,000
Supplemental fuses: filled-tube, cartridge enclosed				
7012540	-	0.1-1	700Vac	50000
		1.25-2	700Vac	50000
		2.25-5	600Vac	50000
		6.3-10	600Vac	50000
		12.5-25	500Vac	50000
Supplemental fuses: filled-tube, surface mount "160020"				
160020	20 x 5.8 x 5.8 (0.79 x 0.23 x 0.23)	3.15-20	250Vdc	1500
		3.15-16	277Vac	1500
		20-20	250Vac	1500
Supplemental fuses: filled-tube, surface mount				
7002563.16 SMD	6.3 x 32 (0.25 x 1.26)	16-16	250Vac	2000
		16-16	300Vdc	2000

7002563.16AK	6.3 x 32 (0.25 x 1.26)	16-16	250Vac	2000
		16-16	300Vdc	2000
7002563.16AK-SA	6.3 x 32 (0.25 x 1.26)	16-16	250Vac	2000
		16-16	300Vdc	2000
7012565.SMD	32 x 6.3 (1.26 x 0.25)	10-16	530Vac	5000
Supplemental micro fuses: filled-tube				
160000	4.4 x 8.0 (0.17 x 0.31)	0.032-5	250Vac	100
		0.032-5	72Vdc	100
7006585, 7006585.SMD	-	6.3-20	500Vac	1,500
Supplemental micro fuses: surface mount				
157000	2.6 x 6.1 (0.10 x 0.24)	0.062-7.0	125Vac	50
		0.062-7.0	125Vdc	50
		8-15	65Vac	50
		8-15	65Vdc	50
158000	2.6 x 6.1 (0.10 x 0.24)	0.25-6.3	65Vdc	50
		0.25-6.3	125Vac	50
		0.25-6.3	32Vdc	300
159000 (+)	2.6 x 6.1 (0.10 x 0.24)	0.315-0.57	250Vac	10
7016974	2.6 x 6.1 (0.10 x 0.24)	0.062-7	125Vac	50
		0.062-7	125Vdc	50
		8-15	65Vac	50
		8-15	65Vdc	50
7016975	2.6 x 6.1 (0.10 x 0.24)	0.25-6.3	65Vdc	50
		0.25-6.3	125Vac	50
		0.25-6.3	32Vdc	300
Supplemental micro fuses: surface mount, cartridge enclosed				

169000.AM	8 x 4.4 x 4.399 (0.31 x 0.17 x 0.17)	0.63-6.3	250Vac	20
------------------	---	----------	--------	----

(+) - Followed by ampere rating

[Click here to view the Colombia Market Access Certification](#)

[Click here to view the Ecuador Market Access Certification](#)

Marking: Company name or trademark , model designation and the Recognized Component Mark for Canada, .

Last Updated on 2021-08-18

The appearance of a company's name or product in this database does not in itself assure that products so identified have been manufactured under UL's Follow-Up Service. Only those products bearing the UL Mark should be considered to be Certified and covered under UL's Follow-Up Service. Always look for the Mark on the product.

UL permits the reproduction of the material contained in the Online Certification Directory subject to the following conditions: 1. The Guide Information, Assemblies, Constructions, Designs, Systems, and/or Certifications (files) must be presented in their entirety and in a non-misleading manner, without any manipulation of the data (or drawings). 2. The statement "Reprinted from the Online Certifications Directory with permission from UL" must appear adjacent to the extracted material. In addition, the reprinted material must include a copyright notice in the following format: "© 2022 UL LLC"