



JDYX2.E19180 Fuses, Supplemental - Component

[Page Bottom](#)

Fuses, Supplemental - Component

[See General Information for Fuses, Supplemental - Component](#)

COOPER BUSSMANN LLC
114 OLD STATE RD
ELLISVILLE, MO 63021 USA

E19180

Supplemental fuses

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
1A6267	-	7.1 - 30	32Vac	1000
74D, 74E, 74F, 74J	6.1 x 31 (0.24 x 1.22)	7.5 - 20	60Vdc	1000
AGA	6.35 x 15.9 (0.25 x 0.63)	4 - 30	32Vac	1000
		4 - 5	125Vac	200
		12 - 30	125Vac	100
AGC	6.35 x 31.8 (0.25 x 1.25)	12 - 17.5	32Vac	1000
		20	32Vac	1000
		25	32Vac	1000
		30	32Vac	1000
		30	125Vac	200
		30	250Vac	100
		35	32Vac	1000
		40	32Vac	1000
AGC-30, AGC-R-30	6.35 x 31.8 (0.25 x 1.25)	12 - 30	250Vac	100
		12 - 30	125Vac	200
		12 - 30	32Vac	300
AGD	-	3 - 12	32Vac	1000
AGX	6.35 x 25.4 (0.25 x 1.00)	12 - 20	125Vac	200
		12 - 20	250Vac	200
		25 - 30	125Vac	100
C310FC-4-R	3.6 x 10 (0.14 x 0.39)	4	125Vac	40
		4	250Vac	40
C310FC-5-R	3.6 x 10 (0.14 x 0.39)	5	125Vac	50
		5	250Vac	50
C310FC-500-R, C310FC-630-R, C310FC-800-R, C310FC-1-R, C310FC-1.25-R, C310FC-1.6-R, C310FC-2-R, C310FC-2.5-R, C310FC-3.15-R				

	3.6 x 10 (0.14 x 0.39)	0.5 - 3.15	125Vac	35
		0.5 - 3.15	250Vac	35
C310FC-6.3-R	3.6 x 10 (0.14 x 0.39)	6.3	125Vac	63
		6.3	250Vac	63
C310T2.5A	10 x 3.6 (0.39 x 0.14)	2.5	125Vac	35
		2.5	250Vac	35
C310T3.15A	10 x 3.6 (0.39 x 0.14)	3.15	125Vac	35
		3.15	250Vac	35
C310T315mA, C310T400mA, C310T500mA, C310T630mA, C310T800mA, C310T1A, C310T1.25A, C310T1.6A, C310T2A				
	4.0 x 11.5 (0.16 x 0.45)	0.315 - 2	125Vac	35
		0.315 - 2	250Vac	35
C310T4A	10 x 3.6 (0.39 x 0.14)	4	125Vac	40
		4	250Vac	40
C310T5A	10 x 3.6 (0.39 x 0.14)	5	125Vac	50
		5	250Vac	50
C310T6.3A	10 x 3.6 (0.39 x 0.14)	6.3	125Vac	60
		6.3	250Vac	60
C517, C517-xxx-R, TDC517, TDC517-R				
	-	2 - 3	350Vac	100
C519, C519-xxx-R	4.25 x 15 (0.17 x 0.59)	0.35	600Vac	25
GKB	7.0 x 46.43 (0.28 x 1.83)	10	300Vdc	1000
		10	125Vac	10000
GLD, GBA	-	6	125Vac	1000
		8 - 15	50Vac	300
		8 - 15	50Vdc	300
GMC, GMC-xxx-R	5 x 20 (0.20 x 0.79)	6.4 - 10	125Vac	200
MDL+, MDL-R+	6.35 x 31.75 (0.25 x 1.25)	9 - 20	32Vac	1000
MDL, MDL-R	-	20 - 30	32Vac	1000
MDL, MDL-R (8.1A - 15A)				
	6.35 x 31.75 (0.25 x 1.25)	8.1 - 15	32Vac	1000
MDQ	-	7.1 - 30	32Vac	1000
MKC	-	0.0625	125Vac	-
MRCHV, MCRHV250V, MCRF125V				
	-	3.15 - 10	125Vac	30
		3.15 - 10	250Vac	30
		12 - 15	72Vac	30
		20	60Vdc	50

		0.1 - 0.315	250Vac	30
OW2237	-	0.75	600Vdc	50000
S520, S520-xxx-R	5 x 20 (0.20 x 0.79)	12.5	250Vac	1500
		12.5	400Vdc	150
TDC518, C518, C518-xxx-R, C520, C520-xxx-R				
	-	0.1 - 0.75	125Vac	10000
		0.1 - 0.75	250Vac	35
		1.5 - 3.5	125Vac	10000
		1.5 - 3.5	250Vac	100
		4 - 5	125Vac	10000
		4 - 5	250Vac	200

Supplemental fuses: pigtail leads

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
AGA-V, AGA-V-R	-	5.1 - 12	32Vac	-
AGC-V	7 x 32.6 (0.28 x 1.28)	12 - 17.5	32Vac	1000
		20	32Vac	1000
		25	32Vac	1000
		30	32Vac	1000
		30	125Vac	200
		30	250Vac	100
		35	32Vac	1000
		40	32Vac	1000
AGC-V+, AGC-V-R+	-	0 - 10	32Vac	-
AGX-V, AGX-V-R	-	5.1 - 20	32Vac	-
C515, C515-xxx-R, TDC515				
	4.25 x 15 (0.17 x 0.59)	0.35	600Vac	25
MDL-V	-	20 - 30	32Vac	1000
MDL-V+, MDL-V-R+	-	8.1 - 30	32Vac	-
MDQ-V, MDQ-V-R	-	8.1 - 30	32Vac	-
S520-V, S520-V-xxx-R	5 x 20 (0.20 x 0.79)	12.5	250Vac	1500
		12.5	400Vdc	150

Supplemental fuses: pigtail leads, cartridge enclosed

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
GDB-V, GDB-V-xxx-R	5 x 20 (0.20 x 0.79)	0.16 - 0.8	250Vac	35
		1 - 6.3	250Vac	63
		8	250Vac	35
		10	250Vac	35
GDC-V, GDC-V-xxx-R	5 x 20 (0.20 x 0.79)	0.032 - 0.16	250Vac	35
		0.2 - 0.4	250Vac	35

GDC-V, GDC-V-xxx-R (0.5A - 10A)				
	5 x 20 (0.20 x 0.79)	8.0 - 10	250Vac	35
		0.5	250Vac	35
		0.63	250Vac	35
		1.0 - 3.15	250Vac	35
		4.0 - 6.3	250Vac	35
GMA-V, GMA-V-xxx-R	5 x 20 (0.20 x 0.79)	7 - 10	125Vac	200
		12 - 15	125Vac	150
GMC-V, GMC-V-xxx-R	5 x 20 (0.20 x 0.79)	6.4 - 10	125Vac	200
GMD-V, GMD-V-xxx-R	5 x 20 (0.20 x 0.79)	3.1 - 4	125Vac	10000
		3.1 - 4	250Vac	200
S500-V, S500-V-xxx-R	5 x 20 (0.20 x 0.79)	0.16 - 0.8	250Vac	35
		1 - 6.3	250Vac	63
		8	250Vac	35
		10	250Vac	35
S506-V, S506-V-xxx-R	5 x 20 (0.20 x 0.79)	8.0 - 10	250Vac	35
		12 - 15	250Vac	150
		0.5	250Vac	35
		0.63 - 0.8	250Vac	35
		1.0 - 3.15	250Vac	35
		4.0 - 6.3	250Vac	35
S506-V-xxx-R	5 x 20 (0.20 x 0.79)	0.032 - 0.16	250Vac	35
		0.2 - 0.4	250Vac	35
TDC515, C515, C515-xxx-R				
	5.2 x 15 (0.20 x 0.59)	3.5 - 7.0	125Vac	400
		3.5 - 7.0	350Vac	100

Supplemental fuses: pigtail leads, filled-tube

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
ABC-V, ABC-V-R	6.35 x 31.75 (0.25 x 1.25)	18	125Vac	1000
		18	250Vac	400
		20	125Vac	1000
		20	250Vac	400
		20	125Vdc	10000
		25	125Vac	1000
		25	125Vac	10000
		25	125Vdc	400
		25	75Vdc	1000
		30	125Vac	1000

		30	125Vac	10000
		30	125Vdc	400
		30	75Vdc	1000
		25	250Vac	200
		30	250Vac	200
C308F-V-xxx	3.14 x 8.7 (0.12 x 0.34)	.04 - .08	250Vac	1500
		.04 - .08	250Vac	4000
		.04 - .08	250Vdc	4000
		.1 - .25	250Vac	1500
		.1 - .25	250Vac	4000
		.1 - .25	250Vdc	4000
		.04 - .08	250Vac	1500
		.04 - .08	250Vac	1500
C310FH-2.0-R	3.6 x 10 (0.14 x 0.39)	1.25 - 2.0	250Vac	150
MDA-V-xxxA+, MDA-V-xxxA-R				
	6.35 x 31.75 (0.25 x 1.25)	25 - 30	125Vac	10000
		25 - 30	250Vac	1500
		25 - 30	125Vdc	10000
		25 - 30	250Vac	60
		25 - 30	125Vdc	60
MDH-V-xxx-R	0.420 x 31.75 (0.02 x 1.25)	21	600Vac	200
		21	150Vdc	200
		25	420Vdc	400

Supplemental fuses: pigtail leads, filled-tube, cartridge enclosed

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
GBH-VxxxA6F	6.35 x 31.25 (0.25 x 1.23)	10 - 20	500Vac	50000
GBH-VxxxA6F, FWH-xxxA6F(#)				
	6.35 x 31.25 (0.25 x 1.23)	25 - 30	500Vac	20000
GBH-xxxA6F, FWH-xxxA6F(#)				
	6.35 x 31.25 (0.25 x 1.23)	10 - 20	600Vac	100000
GDA-V, GDA-V-xxx-R	5 x 20 (0.20 x 0.79)	2 - 6.3	300Vac	100
		0.05	250Vac	100
		0.063 - 0.25	250Vac	100
		0.315 - 0.4	250Vac	100
		0.5 - 0.8	250Vac	100
		1.0 - 6.3	250Vac	100
		8 - 10	250Vac	200
S501-V, S501-V-xxx-R	5 x 20 (0.20 x 0.79)	2 - 6.3	300Vac	100

		8 - 10	250Vac	200
		0.05	250Vac	100
		0.063 - 0.25	250Vac	100
		0.315 - 0.4	250Vac	100
		0.5 - 0.8	250Vac	100
		1.0 - 6.3	250Vac	100
TCP70-V-xxx-R	5.75 x 23.55 (0.23 x 0.93)	30	70Vdc	2500

Supplemental fuses: pigtail leads, time delay, filled-tube

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
S505SCH-XXX-R	5 x 20 (0.20 x 0.79)	3.15 - 6.3	250Vac	1500
S515-V, S515-V-xxx-R	5 x 20 (0.20 x 0.79)	1 - 2.5	250Vac	1500
		3.15	250Vac	1500
		4 - 5	250Vac	1500
		6.3 - 10	250Vac	1500
		1 - 2.5	600Vac	100
		3.15	600Vac	100
		4 - 5	600Vac	100
		6.3 - 10	500Vac	100
TDS505-V, S505-V, S505-V-xxx-R				
	5 x 20 (0.20 x 0.79)	8	250Vac	1500
		10 - 12	250Vac	1000

Supplemental fuses: pigtail leads, time delay, filled-tube, cartridge enclosed

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
S505-V, S505-V-xxx-R, TDS505-V				
	5 x 20 (0.20 x 0.79)	0.5 - 0.8	250Vac	1500
		1.0 - 3.0	250Vac	1500
		3.1 - 3.15	250Vac	1500
		4.0 - 5.0	250Vac	1500
		6.3	250Vac	1500
		0.5 - 0.8	250Vac	100
		1.0 - 3.0	250Vac	100
		3.1 - 3.15	250Vac	100
		4.0 - 5.0	250Vac	100
S505-V, S505-V-xxx-R, TDS505-V (Alt.)				
	5 x 20 (0.20 x 0.79)	1.0	250Vac	100
		1.0	250Vac	1500
S505SC-xxx-R	5 x 20 (0.20 x 0.79)	1 - 3	250Vac	1500
		3.15	250Vac	1500

		4 - 5	250Vac	1500
		6.3 - 10	250Vac	1500

Supplemental fuses: cartridge enclosed

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
C519, C519-xxx-R	5.2 x 15 (0.20 x 0.59)	3.5 - 7.0	125Vac	400
			350Vac	100
GDB, GDB-xxx-R	5 x 20 (0.20 x 0.79)	0.16 - 0.8	250Vac	35
			250Vac	63
			250Vac	35
			250Vac	35
GDC, GDC-xxx-R	5 x 20 (0.20 x 0.79)	8.0 - 10	250Vac	35
			250Vac	35
			250Vac	35
			250Vac	35
			250Vac	35
			250Vac	35
GDC, GDC-xxx-R, GDC-R				
	5 x 20 (0.20 x 0.79)	0.032 - 0.16	250Vac	35
		0.2 - 0.4	250Vac	35
GMA, GMA-xxx-R	5 x 20 (0.20 x 0.79)	7 - 10	125Vac	200
			125Vac	150
GMD, GMD-xxx-R	5 x 20 (0.20 x 0.79)	3.1 - 4	125Vac	10000
			250Vac	200
S500, S500-xxx-R, TDS500				
	5 x 20 (0.20 x 0.79)	0.16 - 0.8	250Vac	35
		1 - 6.3	250Vac	63
		8	250Vac	35
		10	250Vac	35
S506, S506-R	5 x 20 (0.20 x 0.79)	0.032 - 0.16	250Vac	35
			250Vac	35
TDS506, S506, S506-xxx-R				
	5 x 20 (0.20 x 0.79)	12 - 15	250Vac	150
		0.5	250Vac	35
		0.63 - 0.8	250Vac	35
		1.0 - 3.15	250Vac	35
		4.0 - 6.3	250Vac	35
		8.0 - 10	250Vac	35

Supplemental fuses: filled-tube

--	--	--	--	--

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
ABC, ABC-R	6.35 x 31.75 (0.25 x 1.25)	18	125Vac	1000
		18	250Vac	400
		20	125Vac	1000
		20	250Vac	400
		20	125Vdc	10000
		25	125Vac	1000
		25	125Vac	10000
		25	125Vdc	400
		25	75Vdc	1000
		30	125Vac	1000
		30	125Vac	10000
		30	125Vdc	400
		30	75Vdc	1000
		25	250Vac	200
		30	250Vac	200
C310FC-xxx-R	3.6 x 10 (0.14 x 0.39)	0.5 - 6.3	250Vac	35
		0.5 - 6.3	250Vac	10x Ampere rating
DMM, DMM-B, DMM-R	10.31 x 35 (0.41 x 1.38)	0.44	1000Vac	10000
		0.44	1000Vdc	10000
DMM-11A, DMM-B-11A, DMM-11A-R				
	10.31 x 38.1 (0.41 x 1.50)	11	1000Vac	20000
		11	1000Vdc	20000
MDA-xxxA+, MDA-xxxA-R+				
	6.35 x 31.75 (0.25 x 1.25)	25 - 30	125Vac	10000
		25 - 30	250Vac	1500
		25 - 30	125Vdc	10000
		25 - 30	250Vac	60
		25 - 30	125Vdc	60
TCP70-S	6.3 x 25.4 (0.25 x 1.00)	3.15 - 5	70Vdc	2500
		6 - 40	70Vdc	2500
TDC600, TDC600-R	6.3 x 25.4 (0.25 x 1.00)	2	600Vac	200
		10	600Vac	200
		2	250Vac	10000
		10	250Vac	10000

Supplemental fuses: filled-tube, cartridge enclosed

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
GBH-xxxA6F (#)	6.35 x 31.25 (0.25 x 1.23)	25 - 30	500Vac	20000

GDA, GDA-xxx-R	5 x 20 (0.20 x 0.79)	2 - 6.3	300Vac	100
		0.05	250Vac	100
		8 - 10	250Vac	200
		0.063 - 0.25	250Vac	100
		0.315 - 0.4	250Vac	100
		0.5 - 0.8	250Vac	100
		1.0 - 6.3	250Vac	100
MDH-xxx-R	0.420 x 31.75 (0.02 x 1.25)	21	600Vac	200
		21	150Vdc	200
		25	420Vdc	400
S501, S501-xxx-R, TDS501				
	5 x 20 (0.20 x 0.79)	2 - 6.3	300Vac	100
		0.05	250Vac	100
		0.063 - 0.25	250Vac	100
		0.315 - 0.4	250Vac	100
		0.5 - 0.8	250Vac	100
		1.0 - 6.3	250Vac	100
		8 - 10	250Vac	200
TCP70-R	6.3 x 25.2 (0.25 x 0.99)	6 - 10	70Vdc	2500
		3.15 - 5	70Vdc	2500
		12.5 - 15	70Vdc	2500
		25 - 30	70Vdc	2500
		35 - 40	70Vdc	2500
		40	250Vac	2000

Supplemental fuses: paper tube

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
70A, 70H, 70I, 70J, 70L, 70M, 70N				
	-	2.0 - 10	300Vdc	1000
		2.0 - 10	125Vdc	10000
		2.0 - 10	125Vac	10000
70B, 70C, 70D	-	2.0 - 8.0	300Vdc	1000
		2.0 - 8.0	125Vdc	10000
		2.0 - 8.0	125Vac	10000
70E, 70F, 70G	-	0.18 - 0.5	300Vdc	1000
		0.18 - 0.5	125Vac	10000
		0.18 - 0.5	125Vdc	10000
70K, 70P, 70R, 70X	-	0.1 - 0.25	300Vdc	1000
		0.1 - 0.25	125Vdc	10000
		0.1 - 0.25	125Vac	10000
74A, 74B, 74C, 74G, 74H				
		1.25 - 5.0	60Vdc	1000

	6.2 x 31 (0.24 x 1.22)			
80B, 80C	6.35 x 31.75 (0.25 x 1.25)	2 - 3	125Vac	10000
		2 - 3	160Vdc	1500
		2 - 3	65Vdc	3000
80D	6.35 x 31.75 (0.25 x 1.25)	5	125Vac	10000
		5	160Vdc	1500
		5	65Vdc	3000
80G, 80H, 80M	6.35 x 31.75 (0.25 x 1.25)	0.5 - 1.33	125Vac	10000
		0.5 - 1.33	160Vdc	1500
		0.5 - 1.33	65Vdc	3000
GLD, GBA	-	6	125Vac	1000

Supplemental fuses: surface mount

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
1025HC, 1025HCxx-R	10 x 1.7 x 3.14 (0.39 x 0.07 x 0.12)	20 - 30	125Vac	100
		20 - 30	72Vdc	500
		40	125Vac	100
		40	72Vdc	500
		50	60Vdc	600

Supplemental fuses: time delay, filled-tube

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
S515, S515-xxx-R	5 x 20 (0.20 x 0.79)	6.3 - 10	250Vac	1500
		4 - 5	600Vac	100
		6.3 - 10	500Vac	100
		1 - 2.5	250Vac	1500
		3.15	250Vac	1500
		4 - 5	250Vac	1500
		1 - 2.5	600Vac	100
		3.15	600Vac	100
TDS505, SG5013, S505, S505-xxx-R				
	5 x 20 (0.20 x 0.79)	8	250Vac	1500
		10 - 12	250Vac	1000

Supplemental fuses: time delay, filled-tube, cartridge enclosed

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
S505, S505-xxx-R, TDS505, SG5013				
	5 x 20 (0.20 x 0.79)	0.5 - 0.8	250Vac	1500
		1.0 - 3.0	250Vac	1500
		3.1 - 3.15	250Vac	1500

		4.0 - 5.0	250Vac	1500
		6.3	250Vac	1500
		0.5 - 0.8	250Vac	100
		1.0 - 3.0	250Vac	100
		3.1 - 3.15	250Vac	100
		4.0 - 5.0	250Vac	100
S505, S505-xxx-R, TDS505, SG5013 (Alt.)				
	5 x 20 (0.20 x 0.79)	1.0	250Vac	100
		1.0	250Vac	1500

Supplemental micro fuses

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
3216TD, 3216TD-R	-	6.3 - 12	32Vac	35
		6.3 - 12	32Vdc	35
6125FFxxx-R	2.54 x 5.94 (0.10 x 0.23)	0.25 - 15	125Vac	50
		0.25 - 15	72Vdc	50
		0.25 - 15	32Vdc	300
6125T	-	0.625	125Vac	50
		0.625	60Vdc	50
6125TD5A-T	-	0.5 - 5	125Vac	50
		0.5 - 5	60Vdc	50
C308F40mA, C308F50mA, C308F80mA, C308F100mA, C308F125mA, C308F160mA, C308F200mA, C308F250mA				
	3.05 x 8.7 (0.12 x 0.34)	0.04 - 0.16	125Vac	1500
		0.04 - 0.16	250Vac	4000
		0.04 - 0.16	250Vdc	4000
		0.2 - 0.25	125Vac	1500
		0.2 - 0.25	250Vac	4000
		0.2 - 0.25	250Vdc	4000
		0.125	125Vac	1500
		0.125	250Vac	4000
		0.125	250Vdc	4000
		0.125	125Vac	1500
		0.125	250Vac	1500
		0.125	250Vac	1500
		0.04 - 0.16	250Vac	1500
C310T-SC-xxx-R	3.6 x 10 (0.14 x 0.39)	8	250Vac	10x Ampere rating
CC06HxxA, CC06SxxA, CC06MxxA				
	1.6 x 0.8 x 0.4 (0.06 x 0.03 x 0.02)	1 - 3.5	32Vdc	50
		4 - 8	32Vdc	50
		8	24Vdc	80
CC12HxxxA	3.2 x 1.6 x 0.6 (0.13 x 0.06 x 0.02)	0.2	125Vac	50

		0.2	125Vdc	50
		1 - 3	63Vdc	50
		3.5 - 4.0	63Vdc	50
		4.5 - 5	32Vdc	100
		0.5 - 0.75	63Vdc	50
		10 - 20	32Vdc	100
		0.25 - 0.375	63Vdc	50
		6 - 8	32Vdc	200
		6 - 8	32Vdc	200
		10 - 25	32Vdc	200
		30	32Vdc	200
CC12MxxA, 3216FFxx-R	3.2 x 1.6 x 1.0 (0.13 x 0.06 x 0.04)	10 - 20	24Vdc	150
		25	24Vdc	250
		30	24Vdc	300
GMW	-	0 - 0.1	125Vac	35
		0.2 - 5.0	125Vac	35
MCRHV	-	0.1 - 10	250Vac	-
MCRS	-	0.05 - 7	125Vac	50
		0.05 - 7	125Vdc	300
MCRT	2.42 x 7.1 (0.10 x 0.28)	0.1 - 7	125Vac	30
		0.1 - 7	250Vac	30
MCRW	-	0.05 - 15	125Vac	50
		0.05 - 15	125Vdc	300
PCB, PCC, PCH	8.89 x 8.89 x 4.67 (0.35 x 0.35 x 0.18)	0.5 - 2.5	125Vac	10000
		0.5 - 2.5	250Vac	50
		0.5 - 2.5	450Vdc	300
		0.5 - 2.5	450Vdc	5900
		2.6 - 3.0	125Vac	10000
		2.6 - 3.0	250Vac	50
		2.6 - 3.0	450Vdc	300
		2.6 - 3.0	450Vdc	4400
		4	125Vac	10000
		4	250Vdc	300
		4	250Vdc	4200
		4	450Vdc	300
		4	450Vdc	2500
PCD, PCE, PCI	8.89 x 8.89 x 4.67 (0.35 x 0.35 x 0.18)	0.5 - 2.5	125Vac	10000
		0.5 - 2.5	450Vdc	300
		0.5 - 2.5	450Vdc	5900
		2.6 - 3.0	125Vac	10000
		2.6 - 3.0	350Vdc	300
		2.6 - 3.0	350Vdc	4400

		3.1 - 5.0	125Vac	10000
		3.1 - 5.0	250Vdc	300
		3.1 - 5.0	250Vdc	4200
		3.1 - 5.0	400Vdc	300
		3.1 - 5.0	400Vdc	1000
PCG, PCL	8.89 x 8.89 x 4.67 (0.35 x 0.35 x 0.18)	3.1 - 5.0	125Vac	10000
		3.1 - 5.0	250Vdc	300
		3.1 - 5.0	250Vdc	4200
		3.1 - 5.0	400Vdc	300
		3.1 - 5.0	400Vdc	1000
PCJ	8.89 x 8.89 x 4.67 (0.35 x 0.35 x 0.18)	0.5 - 1	125Vac	10000
		0.5 - 1	250Vac	50
		0.5 - 1	750Vdc	300@
		0.5 - 1	750Vdc	3000@
PCK, PCF	8.89 x 8.89 x 4.67 (0.35 x 0.35 x 0.18)	0.5 - 2.5	125Vac	10000
		0.5 - 2.5	250Vac	50
		0.5 - 2.5	450Vdc	300
		0.5 - 2.5	450Vdc	5900
		2.6 - 3.0	125Vac	10000
		2.6 - 3.0	250Vac	50
		2.6 - 3.0	450Vdc	300
		2.6 - 3.0	450Vdc	4400
SS-5	8.6 x 4.3 x 8.4 (0.34 x 0.17 x 0.33)	0.2 - 0.4	250Vac	35
		0.5 - 3.15	250Vac	35
		5.0	250Vac	10 x Ampere Rating
		4.0	250Vac	10 x Ampere Rating
		6.3	250Vac	10 x Ampere Rating
TCP1.25A, TCP1.25-R, F1250T				
	-	1.25	250Vac	50
		1.25	600Vac	60
TCP2A, TCP2-R, F1251T				
	-	2.0	600Vac	60
		2.0	250Vac	50
TCP500mA, TCP500-R, F0500T				
	-	0.5	600Vac	40
		0.5	250Vac	50
TEL	3.1 x 10.16 (0.12 x 0.40)	0.35	600Vdc	6

Supplemental micro fuses: pigtail leads

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
GFA	3.2 x 7.62 (0.13 x 0.30)	0.5 - 5	125Vac	50

SR-5	-	0.04 - 0.16	250Vac	35
		0.2 - 0.4	250Vac	35
		0.5 - 3.15	250Vac	35
		5.0	250Vac	10 x Ampere Rating
		4.0	250Vac	10 x Ampere Rating
		6.3	250Vac	10 x Ampere Rating

Supplemental micro fuses: pigtail leads, filled-tube

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
C310FH-xxx-R (a)	3.6 x 10 (0.14 x 0.39)	1.25 - 2	125Vac	35
		1.25 - 2	250Vac	35
		1.25 - 2	250Vac	200
		1.25 - 2	250Vac	100

Supplemental micro fuses: filled-tube

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
SR-5H	8.4 x 9.2 (0.33 x 0.36)	0.4	300Vac	100
		0.5 - 4.0	300Vac	100
		5.0	300Vac	100
		0.4	250Vac	100
		0.5 - 4.0	250Vac	100
		5.0	250Vac	100
SS-5H	8.6 x 4.3 x 8.4 (0.34 x 0.17 x 0.33)	1 - 4	300Vac	100
		5	300Vac	100
		6.3	300Vac	100
		1 - 4	250Vac	100
		5	250Vac	100
		6.3	250Vac	100

Supplemental micro fuses: surface mount

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
0603FA, 0603FAxxx-R, 0603FA-T				
	0.8 x 1.6 (0.03 x 0.06)	0.25 - 0.375	50Vdc	50
		0.5	50Vdc	35
		0.5 - 1.25	32Vac	50
		0.5 - 1.25	32Vdc	50
		1.5 - 5	32Vac	35
		1.5 - 5	32Vdc	35
		2.1 - 5	24Vdc	35
1025FA, 1025FAxxx-R	-	0.25 - 5	250Vac	50
		0.25 - 5	125Vdc	50
		7 - 10	250Vac	50

		7 - 10	60Vdc	50
		12 - 15	250Vac	50
		12 - 15	60Vdc	50
1025TD, 1025TDxxx-R	-	0.25 - 5	250Vac	50
		0.25 - 5	125Vdc	50
1206FA, 1206FA-T	3.2 x 1.6 x 0.9 (0.13 x 0.06 x 0.04)	0.2 - 0.75	63Vdc	50
		1.0	63Vdc	50
		1.1 - 2	48Vdc	50
		2.1 - 4	48Vdc	30
		5 - 7	32Vdc	35
3216171J0369 -R	3.2 x 1.6 x 0.9 (0.13 x 0.06 x 0.04)	17	13.8Vdc	100
3216FF, 3216FF-T, 3216FF-R				
	3.2 x 1.6 x 0.9 (0.13 x 0.06 x 0.04)	1 - 3	32Vac	50
		1 - 3	63Vdc	50
3216FF, 3216FF-T, 3216FFxxx-R				
	3.2 x 1.6 x 0.9 (0.13 x 0.06 x 0.04)	0.25 - 0.75	32Vac	50
		0.25 - 0.75	63Vdc	50
		4 - 7	32Vac	50
		4 - 7	32Vdc	50
3216LV, 3216LVxxx-R	3.2 x 1.6 x 0.9 (0.13 x 0.06 x 0.04)	0 - 1.5	125Vac	50
		0 - 1.5	125Vdc	50
6125TD, 6125TDxxx-R	-	0.5 - 5	125Vac	50
		0.5 - 5	60Vdc	50
		7	125Vac	50
		7	60Vdc	50
CC12PDxxx, CC12PDxxx-R				
	-	0.75 - 3	32Vac	50
		0.75 - 3	63Vdc	50
		4 - 7	32Vac	50
		4 - 7	32Vdc	50

Supplemental micro fuses: time delay

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
C310T-SC-xxx-R	3.6 x 10 (0.14 x 0.39)	2 - 2.5	250Vac	35
		2 - 2.5	250Vac	10x Ampere rating
		3.15 - 5	250Vac	35
		3.15 - 5	250Vac	10x Ampere rating
		6.3	250Vac	35
		6.3	250Vac	10x Ampere rating

- Catalog number may be followed by -R

(a) - Where xxx is 1.25 through 2.

+ - May be provided with the suffix B after the catalog number and before the amp rating.

Note - Suffix R signifies a lead free plating

Conditions of Acceptability.

1. The fuses shall be used within the Recognized ratings as specified.
2. These fuses are intended for mounting in any Listed or Recognized Component Fuseholder of the same rating, but not more than the fuse ratings tabulated.

Marking: Company name or tradename "Buss" and model designation.

Last Updated on 2015-12-04

[Questions?](#)

[Print this page](#)

[Terms of Use](#)

[Page Top](#)

© 2015 UL LLC

The appearance of a company's name or product in this database does not in itself assure that products so identified have been manufactured under UL's Follow-Up Service. Only those products bearing the UL Mark should be considered to be Certified and covered under UL's Follow-Up Service. Always look for the Mark on the product.

UL permits the reproduction of the material contained in the Online Certification Directory subject to the following conditions: 1. The Guide Information, Assemblies, Constructions, Designs, Systems, and/or Certifications (files) must be presented in their entirety and in a non-misleading manner, without any manipulation of the data (or drawings). 2. The statement "Reprinted from the Online Certifications Directory with permission from UL" must appear adjacent to the extracted material. In addition, the reprinted material must include a copyright notice in the following format: "© 2015 UL LLC".