














































































North American Non-locking NEMA Configurations

Use this chart to determine which general purpose NEMA plug or receptacle is needed for specific applications.

	2 pole 2-wire		2 pole 3-wire grounding			3 pole 3-wire		3 pole 4-wire grounding		4-wire
	125V	250V	125V	250V	277V	125/250V	3ø 250V	125/250V	3ø 250V	3ø 120/208V
15A Receptacle	 1-15R		 5-15R	 6-15R	 7-15R		 11-15R	 14-15R	 15-15R	 18-15R
Plug	 1-15P	 2-15P	 5-15P	 6-15P	 7-15P		 11-15P	 14-15P	 15-15P	 18-15P
20A Receptacle		 2-20R	 5-20R	 6-20R	 7-20R	 10-20R	 11-20R	 14-20R	 15-20R	 18-20R
Plug	 1-20P	 2-20P	 5-20P	 6-20P	 7-20P	 10-20P	 11-20P	 14-20P	 15-20P	 18-20P
30A Receptacle		 2-30R	 5-30R	 6-30R	 7-30R	 10-30R	 11-30R	 14-30R	 15-30R	 18-30R
Plug	 1-30P	 2-30P	 5-30P	 6-30P	 7-30P	 10-30P	 11-30P	 14-30P	 15-30P	 18-30P
50A Receptacle			 5-50R	 6-50R	 7-50R	 10-50R	 11-50R	 14-50R	 15-50R	 18-50R
Plug			 5-50P	 6-50P	 7-50P	 10-50P	 11-50P	 14-50P	 15-50P	 18-50P
60A Receptacle								 14-60R	 15-60R	 18-60R
Plug								 14-60P	 15-60P	 18-60P

Information obtained from ANSI/NEMA WD-6 standard. Face and pin sizes not necessarily to scale. For reference only.



U.S.A.
P.O. Box 115, Oskaloosa, IA 52577
United States/Canada, Puerto Rico, Virgin Islands
Toll-Free Phone: (800) 662-2290 • Toll-Free Fax: (800) 645-5360
International
Phone: (641) 673-5000 • Fax: (641) 673-5100

UK
10 Kelvin Drive • Knowlhill, Milton Keynes
Buckinghamshire MK5 8NH
UK, Ireland, Germany, Switzerland, Austria
Freephone: 00800 5566 5566 • Freefax: 00800 5655 5655
International
Phone: +44 (0)1908 295300 • Fax: +44 (0)1908 295301