







Note 1: Recommended diameter for thru-hole (screw/nut combination) hardware mounting method. Other methods will require holes with different dimensions and parameters.

		_
THIS DOCUMENT AND ITS CONTENTS ARE THE PROPRIETARY CONFIDENTIAL PROPERTY OF INTERPOWER CORPORATION, NO USE OR COPIES		I
MAY BE MADE WITHOUT WRITTEN PERMISSION FROM INTERPOWER CORPORATION.		Γ.
		1
		Į
Added dimension information to cutout screw holes and Note 1. DDF	4/10/12	μ
CHANGE DESCRIPTION	DATE	

	DIMENSIONS IN MILLIMETERS		TITLE: Module				
	DRAFT BY: JC DATE: 3-11-	-2002					
	DOACTING		PART				
	DRAFTING APPROVAL: JC DATE: 3-11-	-2002		83110170			
/12	MATERIAL:	DO NO	T SCALE	INTERP□WER			
Έ		SHEET	1 OF 1	CORPORATION			